## Setupinstruction of Barcode driver

1. Please refer below steps for page setup:

General  $\rightarrow$  "Preferences"  $\rightarrow$  "Page Setup"  $\rightarrow$  Click" Edit "to adjust the Label Size(With/Height)

Fo	onts		Tools	Abou	ıt
General	Sharing	Ports	Advanced	Color Management	Securit
-	Xprinte	er XP-370B	M		
Location:					
Comment	:				
Model:	Xprinte	r XP-370Bl	м		
Features					
Color: N	10		Paper a	available:	
	sided: No				*
Double	No				
Double- Staple: I					
Double Staple: I Speed: I	Unknown				
Double Staple: I Speed: I Maximu	Unknown Im resolutio	n: 203 dpi	-		*
Double Staple: I Speed: I Maximu	Unknown ım resolutio	n: 203 dpi	1 Preferences	Print Test F	

Xprinter XP-370BM Prin	nting Preferences	x
Page Setup Graphics Si	ock Options About	
Stock 2		
Name: USER (76.2 n	nm x 101.6 mm)	■
New	Edit	Delete
Preview Orien	ntation 3 Effects	Image
dit Stock	1	
Stock		review
Name: USER		
Type: Die-Cut Labels	4	
Label Size		
Width: 40.0 mm	Height: 30 mm	*
Exposed Liner Widths		
Left: 1.3 mm	Right: 1.3 mm	

2. Please refer below steps for "stock" setup:

General  $\rightarrow$  "Preferences"  $\rightarrow$  "Stock"  $\rightarrow$  (Media Settings)Select the paper type, as follows:

Fo	onts		loois			10000	
ieneral	Sharing	Ports	Advanced	Color M	lanagem	ient	Securit
-	Xprii	nter XP-370BM					
.ocation:							
Comment	:						
Model:	Xprin	ter XP-370BM					
Features	la		Paper a	wailable			
Double	·sided: No		Fahera	Vallable			
Staple: I	No						
Speed: Maximu	Jnknown Im resolut	ion: 203 dai					*
Xprinter	XP-370	OK 3M Printing I	Cancel Preferences		Apply		Help
Xprinter age Setu Media S	XP-3701	OK 3M Printing I iics Stock	Cancel Preferences Options A	bout	Apply		Help
Xprinter age Setu Media S Method	XP-3701 p Graph Jettings	OK 3M Printing I iics Stock Jse Current Pri	Cancel Preferences Options A Inter Setting	bout	Apply		Help
Xprinter age Setu Media S Method Type:	XP-3701 p Graph Settings	OK BM Printing I lics Stock Jse Current Pri abels With Ga	Preferences Options A nter Setting	bout	Apply		Help
Xprinter age Setu Media S Method Type: Gap He	XP-3701 p Graph Settings : L ight: L L and ling	OK BM Printing I aics Stock Jse Current Pri abels With Ga abels With Ga abels With Ga abels With Ga	Preferences Options A inter Setting aps nter Setting aps arks	bout	Apply ffset:	0.0 mr	Help
Xprinter age Setu Media S Method Type: Gap He - Media H Post-Pri	XP-3701 p Graph Settings : ight: L landling C nt Action:	OK BM Printing I alics Stock Jse Current Pri abels With Ga abels With Ga abels With Ma ontinuous Tear Off	Preferences Options A inter Setting aps nter Setting ips arks	bout	Apply ffset:	0.0 mr	Help
Xprinter age Setu Media S Method Type: Gap He - Media H Post-Pri Occurre	XP-3701 p Graph Settings : L ight: L łandling C nt Action: mce:	OK BM Printing I nics Stock Jse Current Pri abels With Ga abels With Ga abels With Ga abels With Ga abels With Ma continuous Tear Off After Every	Cancel Preferences Options A inter Setting aps nter Setting aps arks Page	bout	Apply ffset:	0.0 mr	Help
Xprinter age Setu Media S Method Type: Gap He - Media H Post-Pri Occurre Interval	XP-3701 p Graph settings : light: L landling C nt Action: mce:	OK BM Printing I nics Stock Jse Current Pri abels With Ga abels With Ga abels With Ga abels With Ma ontinuous Tear Off After Every	Preferences Options A inter Setting aps nter Setting aps arks Page ]	bout	Apply ffset:	0.0 mr	Help n
Xprinter age Setu Media S Method Type: Gap He - Media H Post-Pri Occurre Interval - Position	XP-3701 p Graph Settings : light: landling C nt Action: mce: Adjustme	OK BM Printing I nics Stock Jse Current Pri abels With Ga abels With Ga abels With Ga abels With Ma continuous Tear Off After Every	Cancel Preferences Options A inter Setting aps nter Setting aps arks Page ]	bout	Apply ffset:	0.0 mm	n
Xprinter age Setu Media S Method Type: Gap He Gap He Occurre Interval	XP-3701 p Graph Settings : L ight: L landling mce: Adjustme Current P	OK BM Printing I accs Stock Jse Current Pri abels With Ga abels Stratega Stra	Cancel Preferences Options A inter Setting aps nter Setting aps Page ]	bout Feed (	Apply ffset:	0.0 mr	Help n
Xprinter age Setu Media S Method Type: Gap He Gap He Occurre Interval Position Vertical	XP-3701 p Graph Settings : L ight: L landling C nt Action: mce: Adjustme Current P Offset:	OK BM Printing I accs Stock Jse Current Pri abels With Ga abels Stratega After Every	Preferences Options A inter Setting aps references Preferences Pre	bout Feed (	Apply ffset:	0.0 mm	n

3. "Stock"  $\rightarrow$  Media Handling (Post-Print Action: choose "Tear off")

Tear Off: Can continuously print, tear off paper directly.

Peel Off: Print paper one by one, different loading paper.

Media Setting	s				
Method:	Use Current Printer Setting				
Type:	Labels With Gaps	•			
Gap Height:	3.0 mm	Gap Offset:	0.0 mm		
Post-Print Act	ion: Tear Off	.*	1		
Post-Print Act	ion: Tear Off	•	1		
Occurrence:	Use Current Pr None	inter Settings	1		
Interval:	Tear Off Peel Off	2	0.0 mm		
Desition Adius	Cut		]		
Use Curren	amenis nt Printer Settings				
vertical urrse					

4. Click "Options " → "Printer options " to set Print Speed / Darkness , 5 grades of print speed

supported: 50.8mm/s; 76.2mm/s; 101.6mm/s; 127mm/s; 152.4mm/s, The default print speed is 127mm/s, The default darkness is 7, it has 1-15 grades.

Printer Options	inter Settinge
Print Speed: Darkness:	127.00 mm/sec           50.80 mm/sec           76.20 mm/sec           101.60 mm/sec           127.00 mm/sec           152.40 mm/sec
Graphics Format Direct to Buffer: Stored Graphics:	Automatic  Automatic

5. "Stock" → Media Settings (Type: choose "Label With Gaps", Gap Height: 2.0mm)

Gap height means the gap height between labels.

Method:	Use Current Printer S	Setting 🔹		
Гуре:	Labels With Gaps			
Gap Height:	2.0 mm	Gap Offset:	0.0 mm	
Media Handlin	g	×		
<sup>p</sup> ost-Print Acti	on: Tear Off	•	]	
Occurrence:	After Every Page	+	]	
nterval:		Feed Offset:	0.0 mm	
Position Adjust	ments It Printer Settings			
rentical onset				